

OMEGA EU

Off-Grid



- Pure sine wave inverter
- Enhance AC charger to 60A
- Wide battery input range
- Selectable input voltage range for home appliances and personal computers
- Selectable high power charging current
- Configurable AC/Solar input priority via LCD setting
- Compatible to mains voltage or generator power
- Auto restart while AC is recovering
- Overload and short circuit protection
- Smart battery charger design for optimized battery performance
- Cold start function

MODEL	OMEGA EU 1.5K-12	OMEGA EU 1.5K-24	OMEGA EU 3K-24
Rated Power	1500VA/1200W		3000VA/2400W
INPUT			
Voltage	220/230/240 VAC		
Selectable Voltage Range	170-280 VAC (For Personal Computers) 90-280 VAC (For Home Appliances)		
Frequency Range	50 Hz/60 Hz (Auto sensing)		
OUTPUT			
AC Voltage Regulation (Batt. Mode)	220/230/240VAC \pm 5%		
Surge Power	3000VA		6000VA
Efficiency (Peak)	90% ~ 93%		
Transfer Time	10 ms (For Personal Computers) 20 ms (For Home Appliances)		
Waveform	Pure sine wave		
BATTERY			
Battery Voltage	12 VDC		24 VDC
Floating Charge Voltage	13.5 VDC		27 VDC
Overcharge Protection	16 VDC		32 VDC
SOLAR CHARGER & AC CHARGER			
Maximum PV Array Open Circuit Voltage	50 VDC		75 VDC
Maximum Solar Charge Current	50 A		
Maximum AC Charge Current	60A		
Maximum Charge Current	110A		
PHYSICAL			
Dimension, D x W x H (mm)	100 x 272 x 355		
Net Weight (kgs)	6.6		
OPERATING ENVIRONMENT			
Humidity	5% to 95% Relative Humidity(Non-condensing)		
Operating Temperature	-20°C to 55°C		
Storage Temperature	-30°C to 60°C		

Product specifications are subject to change without further notice